

SANY MED 80

Sanitizing of small environments

Our ozone generator **SANY-MED-80** is designated to sanitize and deodorize environments of small dimensions up to a maximum of 80 m³.

SANY MED 80 is light and easy to be carried and it is powered with electric energy through a normal socket. It's provided with a front end with controls and a simple and intuitive times/functions display, and an extractable aspiration filter. It is easy to use because provided with an electrical box, which manages all the process of sanitizing in complete autonomy. Each one of the three programs is different for duration and quantity of generated ozone and it is studied to guarantee the best result in the shortest time possible. In addition to that, the electrical box allows to operate in total safety, because it selects automatically the correct quantity of ozone to input in the place and it optimizes the exposition time in order to avoid damages to objects and surfaces.



Unlike most of sanitizers on the market, **SANY MED 80** is provided with the "Safe System", a device which catches the residual ozone at the end of the program and converts it back to oxygen, allowing to get back to the normal activities inside the place in total safety, as required by the law D.Lgs. 81/2008 Unique Text in the subject of health and safety protection in the working places.



Technical data sheet



Front end with controls and display intervals/functions

Led signal for device in action

Display for visualization of programs

Warning light for device in action

TECHNICAL SPECIFICATIONS:

| | |
|---------------------|---------------------|
| Structure: | ACCIAIO AISI 430 |
| Power supply: | 110/250V – 50/60 Hz |
| Weight: | kg 4,5 |
| Max treated volume: | 80 m ³ |

SANITIZING TREATMENTS:

| | |
|--------------------------------------|-------------------|
| ENVIRONMENTS UP TO 20 M ³ | Duration: 34 Min. |
| ENVIRONMENTS UP TO 50 M ³ | Duration: 50 Min. |
| ENVIRONMENTS UPTO 80 M ³ | Duration: 90 Min. |

